

**Coordination table: PSR Softstarter with Manuel Motor Starter
400 V, 50 kA, IEC/EN 60947-4-2, AC-53-a, Type 1
Starter and MMS in line
Normal Start**

Motor		Softstarter	Manuel Motor Starter		Contactor type		Max. ambient temperature
Rated Output	Max. current	Type	Type	Current setting	Line	By-pass	
(kW)	(A)			(A)			(°C)
0.25	1	PSR3-600-70	MS116-1	0.63 - 1	A9	Integrated	40
0.37	1.6	PSR3-600-70	MS116-1.6	1 - 1.6	A9	Integrated	40
0.55	1.6	PSR3-600-70	MS116-1.6	1 - 1.6	A9	Integrated	40
0.75	2.5	PSR3-600-70	MS116-2.5	1.6 - 2.5	A9	Integrated	40
1.1	3.9	PSR3-600-70	MS116-4	2.5 - 5	A9	Integrated	40
1.5	3.9	PSR3-600-70	MS116-4	2.5 - 4	A9	Integrated	40
2.2	6.3	PSR6-600-70	MS116-6.3	4 - 6.3	A9	Integrated	40
3	6.8	PSR6-600-70	MS116-10	6.3 - 10	A9	Integrated	40
4	9	PSR9-600-70	MS116-10	6.3 - 10	A9	Integrated	40
5.5	12	PSR12-600-70	MS325-12.5	9 - 12.5	A12	Integrated	40
7.5	16	PSR16-600-70	MS325-16	12.5 - 16	A16	Integrated	40
11	25	PSR25-600-70	MS325-25	20 - 25	A26	Integrated	40
15	30	PSR30-600-70	MS450-32	22 - 32	A30	Integrated	40
18.5	37	PSR37-600-70	MS450-37	28 - 40	A40	Integrated	40
22	45	PSR45-600-70	MS450-45	36 - 45	A50	Integrated	40